


AD-A241 078



Fine-Structure Artifact of the
Velocity Distribution of Cs Beam Tubes
as Measured by the
Pulsed Microwave Power Technique

W. A. JOHNSON, S. K. KARUZA, and F. J. VOIT
Electronics Research Laboratory
The Aerospace Corporation
El Segundo, CA 90245-4691

15 October 1990


Prepared for

SPACE SYSTEMS DIVISION
AIR FORCE SYSTEMS COMMAND
Los Angeles Air Force Base
P.O. Box 92960
Los Angeles, CA 90009-2960

91-11980



APPROVED FOR PUBLIC RELEASE;
DISTRIBUTION UNLIMITED





This report was submitted by The Aerospace Corporation, El Segundo, CA 90245, under Contract No. F04701-88-C-0089 with the Space Systems Division, P. O. Box 92960, Los Angeles, CA 90009-2960. It was reviewed and approved for The Aerospace Corporation by M. J. Daugherty, Director, Electronics Research Laboratory.

D. Rojas, Capt, USAF, was the project officer for the Mission-Oriented Investigation and Experimentation (MOIE) Program.

This report has been reviewed by the Public Affairs Office (PAS) and is releasable to the National Technical Information Service (NTIS). At NTIS, it will be available to the general public, including foreign nationals.

This technical report has been reviewed and is approved for publication. Publication of this report does not constitute Air Force approval of the report's findings or conclusions. It is published only for the exchange and stimulation of ideas.

 10 Aug 90
DAN ROJAS, Capt, USAF
MOIE Project Officer
SSD/MSSB


JONATHAN EMMES, Maj, USAF
MOIE Program manager
AFSTC/WCO OL-AB

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE

REPORT DOCUMENTATION PAGE

1a. REPORT SECURITY CLASSIFICATION Unclassified			1b. RESTRICTIVE MARKINGS		
2a. SECURITY CLASSIFICATION AUTHORITY			3. DISTRIBUTION/AVAILABILITY OF REPORT Approved for public release; distribution unlimited.		
2b. DECLASSIFICATION/DOWNGRADING SCHEDULE					
4. PERFORMING ORGANIZATION REPORT NUMBER(S) TR-0090(5925-08)-2			5. MONITORING ORGANIZATION REPORT NUMBER(S) SSD-TR-90-39		
6a. NAME OF PERFORMING ORGANIZATION The Aerospace Corporation Laboratory Operations		6b. OFFICE SYMBOL (If applicable)	7a. NAME OF MONITORING ORGANIZATION Space Systems Division		
6c. ADDRESS (City, State, and ZIP Code) El Segundo, CA 90245			7b. ADDRESS (City, State, and ZIP Code) Los Angeles Air Force Base Los Angeles, CA 90009-2960		
8a. NAME OF FUNDING/SPONSORING ORGANIZATION		8b. OFFICE SYMBOL (If applicable)	9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER F04701-88-C-0089		
8c. ADDRESS (City, State, and ZIP Code)			10. SOURCE OF FUNDING NUMBERS		
			PROGRAM ELEMENT NO.	PROJECT NO.	TASK NO.
			WORK UNIT ACCESSION NO.		
11. TITLE (Include Security Classification) Fine-Structure Artifact of the Velocity Distribution of Cs Beam Tubes as Measured by the Pulsed Microwave Power Technique					
12. PERSONAL AUTHOR(S) Johnson, W. A.; Karuza, S. K.; Voit, F. J.					
13a. TYPE OF REPORT		13b. TIME COVERED FROM _____ TO _____		14. DATE OF REPORT (Year, Month, Day) 15 October 1990	
15. PAGE COUNT 15					
16. SUPPLEMENTARY NOTATION					
17. COSATI CODES			18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)		
FIELD	GROUP	SUB-GROUP	Cesium frequency standards Cesium velocity distributions Pulsed microwave technique		
19. ABSTRACT (Continue on reverse if necessary and identify by block number)					
<p>An artifact of the pulsed microwave power technique used to measure the velocity distributions of Cs beam tubes is a fine structure on the distribution. In previously reported measurements the signal-to-noise ratio was not high enough to show this structure clearly. This paper presents results that show this structure in detail. To predict these results, a simple theory has been used that considers the Ramsey response function (i.e., output tube current vs. microwave frequency) as being a simple electrical-filter transfer function for the input of the pulse-modulated microwave power. Calculations that assume the principle of superposition give predictions that are in close agreement with the measured results. This theory also predicts how to set the pulse width so that the fine-structure artifact is minimized.</p>					
20. DISTRIBUTION/AVAILABILITY OF ABSTRACT			21. ABSTRACT SECURITY CLASSIFICATION		
<input checked="" type="checkbox"/> UNCLASSIFIED/UNLIMITED <input type="checkbox"/> SAME AS RPT. <input type="checkbox"/> DTIC USERS			Unclassified		
22a. NAME OF RESPONSIBLE INDIVIDUAL			22b. TELEPHONE (Include Area Code)		22c. OFFICE SYMBOL

Preface

The authors thank Mr. Michael Meyer of The Aerospace Corporation for editing and preparing this report.



Accession For	
NTIS GRA&I	<input checked="" type="checkbox"/>
DTIC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Distribution/	
Availability Codes	
Dist	Avail and/or Special
A-1	

Contents

Preface	1
I. Introduction	5
II. Discussion	7
III. Measurements	11
IV. Conclusions	13
References	15

Figures

1. Block Diagram of the System for Measuring the Velocity Distribution of the Cs Beam Tube under Pulsed Microwave Conditions	5
2. Operation of the Ramsey Cavity with Pulsed Microwave Power	6
3. Measured Velocity Distribution for a Cs Beam Tube Using a Pulse Width of 37 μ sec and a Peak Microwave Power of 2000 μ W	6
4. The CW Ramsey Patterns of All Seven Transitions in a Cs Beam Tube	7
5. Pulse Modulation Waveform	8
6. Ramsey Response in Relation to the Pulsed Microwave Spectrum for a Narrow Pulse Width	9
7. Main and First Upper Ramsey Response in Relation to the Pulsed Microwave Spectrum	9
8. Ramsey Response in Relation to the Pulsed Microwave Spectrum for a Pulse Width that Places the Spectral Nulls at the Centers of the Upper and Lower Ramsey Responses	10
9. Measured Cs Velocity Distributions for Three Pulse Widths and Peak Microwave Powers, as Indicated. (a) 10 μ sec and 3300 μ W, (b) 26 μ sec and 3300 μ W, and (c) 52 μ sec and 2000 μ W	11

Table

1. Fine-Structure Period $\Delta\nu$ for Three Cs Beam Tubes	12
--	----

I. Introduction

The knowledge of the velocity distribution of a cesium (Cs) beam tube provides considerable insight into the performance and alignment of the beam optics, which in turn affects the final performance of the frequency standard. To measure these velocity distributions, early investigators [1,2,3] developed a method that used the pulsed excitation of atomic beam devices that had Ramsey-type interaction regions; this allowed for the observation of signals that were due to very narrow velocity groups. A completely automatic system that employed this pulsed microwave technique was set up in our laboratories. Figure 1 is a block diagram of the equipment used; the set-up is described in detail in [4].

Figure 2 shows the operation of the Ramsey cavity with pulsed microwave power. For a pulse period of T the velocity v selected is L/T , as shown. The pulse width τ is chosen to be less than the Cs ions' time of flight through the interaction regions, i.e., less than l/v .

In the process of making some of our early velocity-distribution measurements, we noticed what appeared to be a periodic structure on the distribution. At first we thought this structure to be noise in the measurement system; however, as we improved our system further, we could see that the structure was clearly there. The amplitude of this structure was found to be a function of the pulse width. A typical example of the structure is shown in Figure 3, which is a plot of the Cs velocity distribution $\rho(v)$.




Figure 1. Block Diagram of the System for Measuring the Velocity Distribution of the Cs Beam Tube under Pulsed Microwave Conditions




Figure 2. Operation of the Ramsey Cavity with Pulsed Microwave Power. The design of the Ramsey dual-interaction region allows one to select the velocity of the atomic beam by setting the period T of the microwave pulses.




Figure 3. Measured Velocity Distribution for a Cs Beam Tube Using a Pulse Width of $37 \mu sec$ and a Peak Microwave Power of $2000 \mu W$

II. Discussion

The structure shown in Figure 3 can be understood by looking at the pulse-power spectrum and viewing the Ramsey response function as a filter for this spectrum. The Ramsey response for the tube measured in Figure 3 is shown in Figure 4. For a pulse modulation function as shown in Figure 5, the Fourier components are given by

$$F(t) = \sum_{n=0,1,2,3,\dots} A_n \cos 2\pi n \frac{t}{T} \quad (1)$$

where

$$A_0 = \frac{\tau}{T} \quad (2)$$

and

$$A_n = 2 \frac{\tau}{T} \frac{\sin \pi n \frac{\tau}{T}}{\pi n \frac{\tau}{T}}, \quad n = 1, 2, 3, \dots \quad (3)$$




Figure 4. The CW Ramsey Patterns of All Seven Transitions in a Cs Beam Tube




Figure 5. Pulse Modulation Waveform

Each of these components modulates the rf carrier to give a pair of equal components at $f_0 \pm n/T$, where f_0 is the rf carrier. Figure 6 shows this amplitude distribution (which we will refer to as the $\sin x/x$ distribution) in relation to the Ramsey response function. For the particular C-field used for the tube, the separation in the Ramsey responses (i.e., the Zeeman frequency f_z) was 38.86 kHz. The tube length L is ≈ 12.5 cm; therefore, for a velocity of 150 m/sec, the modulation frequency would be ≈ 1200 Hz. There are therefore $38.86/1.2 \approx 33$ components between the component at f_0 and the component at $f_0 + 38.86$ kHz. Figure 6 is drawn for a τ of about 10 μ sec, which places the first null in the $\sin x/x$ distribution at 100 kHz. For ease of illustration, the separations of the pulse components are depicted as much wider than is actually the case.

Figure 7 shows the location of the components for the central Ramsey transition as well as for the first upper transition. Each of the components gives a maximum current and therefore, to the extent that the principle of superposition applies, the output current will be a maximum. The rf frequency is then swept and the component in the output current at the modulation frequency $f_m (= 1/T)$ is then the measure of the density of the atoms in the beam at the velocity v_m , where

$$v_m = Lf_m. \quad (4)$$

The carrier is then reset to f_0 and f_m is changed slightly to $f_m + \Delta f$, to enable one to look at a slightly different velocity, $v_m + \Delta v$. Then

$$\Delta v = L\Delta f. \quad (5)$$

Note that the components close to f_0 change slowly; i.e., the first sideband pair moves by Δf , the second by $2\Delta f$, and so on. However, the components at the first upper transition move very rapidly; i.e., n is very high. If Δf is chosen such that each of the components at the first upper transition moves by f_m , we will again have a maximum-current situation. Then

$$f_m = n\Delta f, \quad (6)$$




Figure 6. Ramsey Response in Relation to the Pulsed Microwave Spectrum for a narrow Pulse Width




Figure 7. Main and First Upper Ramsey Response in Relation to the Pulsed Microwave Spectrum

but

$$n = \frac{f_z}{f_m} \quad (7)$$

Hence

$$\Delta v = L \frac{f_m^2}{f_z} \quad (8)$$

In other words, from these very heuristic arguments a fine-structure velocity period of $L f_m^2 / f_z$ has been predicted.

We should note that although Δv is not a function of the pulse period τ , the amplitude of the structure certainly will be. For example, a pulse that is much narrower than $1/f_z$ will result in a very broad power spectrum (such as that shown in Figure 6) and will consequently yield a large amplitude in the fine structure. Conversely, if the pulse width is chosen so as to put the nulls in the $\sin x/x$ function at the upper Ramsey responses, the effect will be minimized, because a smaller share of the sideband energy is in the upper and lower Ramsey responses. This case is illustrated in Figure 8.




Figure 8. Ramsey Response in Relation to the Pulsed Microwave Spectrum for a Pulse Width that Places the Spectral Nulls at the Centers of the Upper and Lower Ramsey Responses

III. Measurements

The velocity measurement shown in Figure 3 was for a pulse width of $37 \mu\text{sec}$. The Zeeman frequency for this tube was 38.86 kHz and thus the second maximum in the $\sin x/x$ distribution is very close to the first upper and lower Ramsey responses. This pulse width also places the third and fourth maxima in the $\sin x/x$ distribution close to the second and third upper and lower Ramsey responses. Therefore, there should be a clear fine structure, and indeed, this structure is easily seen in Figure 3.

The same tube with the same C-field was measured for a very narrow ($10 \mu\text{sec}$) pulse. This should also result in a clear fine structure. Figure 9(a) shows the results of this measurement. It is a little surprising that the minima of the distribution are so close to zero. This might be because the polarity of the components in the first side lobe in the $\sin x/x$ distribution is reversed from that in the main lobe. Choosing the pulse width such that the first null in the $\sin x/x$ distribution is at the first upper and lower Ramsey responses should result in a minimum structure, and in fact Figure 9(b) shows this result. Similarly, placing the second null at the upper and lower Ramsey responses should also minimize this structure. Figure 9(c) confirms this.




Figure 9. Measured Cs Velocity Distributions for Three Pulse Widths and Peak Microwave Powers, as Indicated. (a) $10 \mu\text{sec}$ and $3300 \mu\text{W}$, (b) $26 \mu\text{sec}$ and $3300 \mu\text{W}$, and (c) $52 \mu\text{sec}$ and $2000 \mu\text{W}$.

Table 1: Fine-Structure Period $\Delta\nu$ for Three Cs Beam Tubes

Tube	τ , μsec	f_z , kHz	Measured, m/sec	Calculated, m/sec
A	37	38.86	4.42	4.29
A	10	38.86	4.59	4.48
B	10	33.43	2.79	2.81
C	20	30.55	3.67	3.79

Table 1 presents a comparison of the measured and calculated [from Eq. (8)] fine-structure periods for the cases shown in Figures 3 and 9(a), as well as for measurements made on two other tubes from two other manufacturers. Each of the tubes is between 12 and 13 cm long. Note that the two calculated $\Delta\nu$ for the two different τ 's for tube A were for two slightly different velocity ranges, and hence are slightly different. In general, the agreement between the calculated and measured Δ 's is excellent.

IV. Conclusions

A fine-structure feature on the velocity distribution of Cs beam tubes, as measured by the pulsed microwave power technique, has been identified and quantified. This feature was shown to result from the existence of large spectral components at the frequencies of the upper and lower Ramsey responses. It has been shown that this feature can be minimized by choosing the pulse width such that the nulls in the microwave power spectrum are at these upper and lower Ramsey responses. Specifically, this means that the pulse width should be chosen to be an integer multiple of the reciprocal of the Zeeman frequency. A simple theory was developed to enable one to predict the fine-structure period as a function of the beam velocity, the tube length, and the Zeeman frequency. This theory employed the concept of the Ramsey response pattern as an electrical filter. This concept may be useful in other tube studies, e.g. those of modulation effects. Also, measurements were presented that demonstrated close agreement between the measured fine-structure period and the calculated one. Finally, it was shown that the fine structure virtually disappears if the pulse period is chosen to be an integer multiple of the reciprocal of the Zeeman frequency.

References

1. H. Hellwig, S. Jarvis, D. Halford, and H. E. Bell, "Evaluation and operation of atomic beam tube frequency standards using time domain velocity selection modulation," *Metrologia*, **9**, 1973, pp. 107-112.
2. H. Hellwig, S. Jarvis, D. J. Glaze, D. Halford, and H. E. Bell, "Time domain velocity selection modulation as a tool to evaluate cesium beam tubes," in *Proceedings of the 27th Annual Symposium on Frequency Control* (Ft. Monmouth, N.J.), June 1973, pp. 356-362.
3. D. A. Howe, H. E. Bell, H. Hellwig, and A. DeMarchi, "Preliminary research and development of cesium beam tube accuracy evaluation system," in *28th Annual Symposium on Frequency Control*, 1974, pp. 362-372.
4. S. K. Karuza, W. A. Johnson, J. P. Hurrell, M. F. Bottjer, and F. J. Voit, "An Automated System for Measuring Velocity Distribution in Cesium Beam Tubes," in *Proceedings of the 4th European Frequency and Time Forum*, Neuchâtel, Switzerland, March 13-15, 1990.

LABORATORY OPERATIONS

The Aerospace Corporation functions as an "architect-engineer" for national security projects, specializing in advanced military space systems. Providing research support, the corporation's Laboratory Operations conducts experimental and theoretical investigations that focus on the application of scientific and technical advances to such systems. Vital to the success of these investigations is the technical staff's wide-ranging expertise and its ability to stay current with new developments. This expertise is enhanced by a research program aimed at dealing with the many problems associated with rapidly evolving space systems. Contributing their capabilities to the research effort are these individual laboratories:

Aerophysics Laboratory: Launch vehicle and reentry fluid mechanics, heat transfer and flight dynamics; chemical and electric propulsion, propellant chemistry, chemical dynamics, environmental chemistry, trace detection; spacecraft structural mechanics, contamination, thermal and structural control; high temperature thermomechanics, gas kinetics and radiation; cw and pulsed chemical and excimer laser development, including chemical kinetics, spectroscopy, optical resonators, beam control, atmospheric propagation, laser effects and countermeasures.

Chemistry and Physics Laboratory: Atmospheric chemical reactions, atmospheric optics, light scattering, state-specific chemical reactions and radiative signatures of missile plumes, sensor out-of-field-of-view rejection, applied laser spectroscopy, laser chemistry, laser optoelectronics, solar cell physics, battery electrochemistry, space vacuum and radiation effects on materials, lubrication and surface phenomena, thermionic emission, photosensitive materials and detectors, atomic frequency standards, and environmental chemistry.

Electronics Research Laboratory: Microelectronics, solid-state device physics, compound semiconductors, radiation hardening; electro-optics, quantum electronics, solid-state lasers, optical propagation and communications; microwave semiconductor devices, microwave/millimeter wave measurements, diagnostics and radiometry, microwave/millimeter wave thermionic devices; atomic time and frequency standards; antennas, rf systems, electromagnetic propagation phenomena, space communication systems.

Materials Sciences Laboratory: Development of new materials: metals, alloys, ceramics, polymers and their composites, and new forms of carbon; nondestructive evaluation, component failure analysis and reliability; fracture mechanics and stress corrosion; analysis and evaluation of materials at cryogenic and elevated temperatures as well as in space and enemy-induced environments.

Space Sciences Laboratory: Magnetospheric, auroral and cosmic ray physics, wave-particle interactions, magnetospheric plasma waves; atmospheric and ionospheric physics, density and composition of the upper atmosphere, remote sensing using atmospheric radiation; solar physics, infrared astronomy, infrared signature analysis; effects of solar activity, magnetic storms and nuclear explosions on the earth's atmosphere, ionosphere and magnetosphere; effects of electromagnetic and particulate radiations on space systems; space instrumentation.